

Convolution solutions (Sect. 6.6).

- ▶ Convolution of two functions.
- ▶ Properties of convolutions.
- ▶ Laplace Transform of a convolution.
- ▶ Impulse response solution.
- ▶ Solution decomposition theorem.

Convolution solutions (Sect. 6.6).

- ▶ **Convolution of two functions.**
- ▶ Properties of convolutions.
- ▶ Laplace Transform of a convolution.
- ▶ Impulse response solution.
- ▶ Solution decomposition theorem.

Convolution of two functions.

Definition

The *convolution* of piecewise continuous functions $f, g : \mathbb{R} \rightarrow \mathbb{R}$ is the function $f * g : \mathbb{R} \rightarrow \mathbb{R}$ given by

$$(f * g)(t) = \int_0^t f(\tau)g(t - \tau) d\tau.$$

Remarks:

- ▶ $f * g$ is also called the generalized product of f and g .
- ▶ The definition of convolution of two functions also holds in the case that one of the functions is a generalized function, like Dirac's delta.

Convolution of two functions.

Example

Find the convolution of $f(t) = e^{-t}$ and $g(t) = \sin(t)$.

Solution: By definition: $(f * g)(t) = \int_0^t e^{-\tau} \sin(t - \tau) d\tau.$

Integrate by parts twice: $\int_0^t e^{-\tau} \sin(t - \tau) d\tau =$

$$\left[e^{-\tau} \cos(t - \tau) \right] \Big|_0^t - \left[e^{-\tau} \sin(t - \tau) \right] \Big|_0^t - \int_0^t e^{-\tau} \sin(t - \tau) d\tau,$$

$$2 \int_0^t e^{-\tau} \sin(t - \tau) d\tau = \left[e^{-\tau} \cos(t - \tau) \right] \Big|_0^t - \left[e^{-\tau} \sin(t - \tau) \right] \Big|_0^t,$$

$$2(f * g)(t) = e^{-t} - \cos(t) - 0 + \sin(t).$$

We conclude: $(f * g)(t) = \frac{1}{2} [e^{-t} + \sin(t) - \cos(t)].$ ◁

Convolution solutions (Sect. 6.6).

- ▶ Convolution of two functions.
- ▶ **Properties of convolutions.**
- ▶ Laplace Transform of a convolution.
- ▶ Impulse response solution.
- ▶ Solution decomposition theorem.

Properties of convolutions.

Theorem (Properties)

For every piecewise continuous functions f , g , and h , hold:

- (i) *Commutativity:* $f * g = g * f$;
- (ii) *Associativity:* $f * (g * h) = (f * g) * h$;
- (iii) *Distributivity:* $f * (g + h) = f * g + f * h$;
- (iv) *Neutral element:* $f * 0 = 0$;
- (v) *Identity element:* $f * \delta = f$.

Proof:

$$(v): (f * \delta)(t) = \int_0^t f(\tau) \delta(t - \tau) d\tau = f(t).$$

Properties of convolutions.

Proof:

(1): Commutativity: $f * g = g * f$.

The definition of convolution is,

$$(f * g)(t) = \int_0^t f(\tau) g(t - \tau) d\tau.$$

Change the integration variable: $\hat{\tau} = t - \tau$, hence $d\hat{\tau} = -d\tau$,

$$(f * g)(t) = \int_t^0 f(t - \hat{\tau}) g(\hat{\tau})(-1) d\hat{\tau}$$

$$(f * g)(t) = \int_0^t g(\hat{\tau}) f(t - \hat{\tau}) d\hat{\tau}$$

We conclude: $(f * g)(t) = (g * f)(t)$. □

Convolution solutions (Sect. 6.6).

- ▶ Convolution of two functions.
- ▶ Properties of convolutions.
- ▶ **Laplace Transform of a convolution.**
- ▶ Impulse response solution.
- ▶ Solution decomposition theorem.

Laplace Transform of a convolution.

Theorem (Laplace Transform)

If f, g have well-defined Laplace Transforms $\mathcal{L}[f], \mathcal{L}[g]$, then

$$\mathcal{L}[f * g] = \mathcal{L}[f] \mathcal{L}[g].$$

Proof: The key step is to interchange two integrals. We start with the product of the Laplace transforms,

$$\mathcal{L}[f] \mathcal{L}[g] = \left[\int_0^\infty e^{-st} f(t) dt \right] \left[\int_0^\infty e^{-s\tilde{t}} g(\tilde{t}) d\tilde{t} \right],$$

$$\mathcal{L}[f] \mathcal{L}[g] = \int_0^\infty e^{-s\tilde{t}} g(\tilde{t}) \left(\int_0^\infty e^{-st} f(t) dt \right) d\tilde{t},$$

$$\mathcal{L}[f] \mathcal{L}[g] = \int_0^\infty g(\tilde{t}) \left(\int_0^\infty e^{-s(t+\tilde{t})} f(t) dt \right) d\tilde{t}.$$

Laplace Transform of a convolution.


Proof: Recall: $\mathcal{L}[f] \mathcal{L}[g] = \int_0^\infty g(\tilde{t}) \left(\int_0^\infty e^{-s(t+\tilde{t})} f(t) dt \right) d\tilde{t}$.

Change variables: $\tau = t + \tilde{t}$, hence $d\tau = dt$;

$$\mathcal{L}[f] \mathcal{L}[g] = \int_0^\infty g(\tilde{t}) \left(\int_{\tilde{t}}^\infty e^{-s\tau} f(\tau - \tilde{t}) d\tau \right) d\tilde{t}.$$

$$\mathcal{L}[f] \mathcal{L}[g] = \int_0^\infty \int_{\tilde{t}}^\infty e^{-s\tau} g(\tilde{t}) f(\tau - \tilde{t}) d\tau d\tilde{t}.$$

The key step: Switch the order of integration.



$$\mathcal{L}[f] \mathcal{L}[g] = \int_0^\infty \int_0^\tau e^{-s\tau} g(\tilde{t}) f(\tau - \tilde{t}) d\tilde{t} d\tau.$$

Laplace Transform of a convolution.

Proof: Recall: $\mathcal{L}[f] \mathcal{L}[g] = \int_0^\infty \int_0^\tau e^{-s\tau} g(\tilde{t}) f(\tau - \tilde{t}) d\tilde{t} d\tau.$

Then, is straightforward to check that

$$\mathcal{L}[f] \mathcal{L}[g] = \int_0^\infty e^{-s\tau} \left(\int_0^\tau g(\tilde{t}) f(\tau - \tilde{t}) d\tilde{t} \right) d\tau,$$

$$\mathcal{L}[f] \mathcal{L}[g] = \int_0^\infty e^{-s\tau} (g * f)(\tau) d\tau$$

$$\mathcal{L}[f] \mathcal{L}[g] = \mathcal{L}[g * f]$$

We conclude: $\mathcal{L}[f * g] = \mathcal{L}[f] \mathcal{L}[g].$

□

Convolution solutions (Sect. 6.6).

- ▶ Convolution of two functions.
- ▶ Properties of convolutions.
- ▶ Laplace Transform of a convolution.
- ▶ **Impulse response solution.**
- ▶ Solution decomposition theorem.

Impulse response solution.

Definition

The *impulse response solution* is the function y_δ solution of the IVP

$$y_\delta'' + a_1 y_\delta' + a_0 y_\delta = \delta(t - c), \quad y_\delta(0) = 0, \quad y_\delta'(0) = 0, \quad c \in \mathbb{R}.$$

Example

Find the impulse response solution of the IVP

$$y_\delta'' + 2y_\delta' + 2y_\delta = \delta(t - c), \quad y_\delta(0) = 0, \quad y_\delta'(0) = 0.$$

Solution: $\mathcal{L}[y_\delta''] + 2\mathcal{L}[y_\delta'] + 2\mathcal{L}[y_\delta] = \mathcal{L}[\delta(t - c)]$.

$$(s^2 + 2s + 2)\mathcal{L}[y_\delta] = e^{-cs} \quad \Rightarrow \quad \mathcal{L}[y_\delta] = \frac{e^{-cs}}{(s^2 + 2s + 2)}.$$

Impulse response solution.

Example

Find the impulse response solution of the IVP

$$y_\delta'' + 2y_\delta' + 2y_\delta = \delta(t - c), \quad y_\delta(0) = 0, \quad y_\delta'(0) = 0, .$$

Solution: Recall: $\mathcal{L}[y_\delta] = \frac{e^{-cs}}{(s^2 + 2s + 2)}$.

Find the roots of the denominator,

$$s^2 + 2s + 2 = 0 \quad \Rightarrow \quad s_\pm = \frac{1}{2} [-2 \pm \sqrt{4 - 8}]$$

Complex roots. We complete the square:

$$s^2 + 2s + 2 = \left[s^2 + 2\left(\frac{2}{2}\right)s + 1 \right] - 1 + 2 = (s + 1)^2 + 1.$$

Therefore, $\mathcal{L}[y_\delta] = \frac{e^{-cs}}{(s + 1)^2 + 1}$.

Impulse response solution.

Example

Find the impulse response solution of the IVP

$$y_\delta'' + 2y_\delta' + 2y_\delta = \delta(t - c), \quad y_\delta(0) = 0, \quad y_\delta'(0) = 0, .$$

Solution: Recall: $\mathcal{L}[y_\delta] = \frac{e^{-cs}}{(s+1)^2 + 1}$.

Recall: $\mathcal{L}[\sin(t)] = \frac{1}{s^2 + 1}$, and $\mathcal{L}[f](s - c) = \mathcal{L}[e^{ct} f(t)]$.

$$\frac{1}{(s+1)^2 + 1} = \mathcal{L}[e^{-t} \sin(t)] \Rightarrow \mathcal{L}[y_\delta] = e^{-cs} \mathcal{L}[e^{-t} \sin(t)].$$

Since $e^{-cs} \mathcal{L}[f](s) = \mathcal{L}[u(t - c) f(t - c)]$,

we conclude $y_\delta(t) = u(t - c) e^{-(t-c)} \sin(t - c)$. \triangleleft

Convolution solutions (Sect. 6.6).

- ▶ Convolution of two functions.
- ▶ Properties of convolutions.
- ▶ Laplace Transform of a convolution.
- ▶ Impulse response solution.
- ▶ **Solution decomposition theorem.**

Solution decomposition theorem.

Theorem (Solution decomposition)

The solution y to the IVP

$$y'' + a_1 y' + a_0 y = g(t), \quad y(0) = y_0, \quad y'(0) = y_1,$$

can be decomposed as

$$y(t) = y_h(t) + (y_\delta * g)(t),$$

where y_h is the solution of the homogeneous IVP

$$y_h'' + a_1 y_h' + a_0 y_h = 0, \quad y_h(0) = y_0, \quad y_h'(0) = y_1,$$

and y_δ is the impulse response solution, that is,

$$y_\delta'' + a_1 y_\delta' + a_0 y_\delta = \delta(t), \quad y_\delta(0) = 0, \quad y_\delta'(0) = 0.$$

Solution decomposition theorem.

Example

Use the Solution Decomposition Theorem to express the solution of

$$y'' + 2y' + 2y = \sin(at), \quad y(0) = 1, \quad y'(0) = -1.$$

Solution: $\mathcal{L}[y''] + 2\mathcal{L}[y'] + 2\mathcal{L}[y] = \mathcal{L}[\sin(at)]$, and recall,

$$\mathcal{L}[y''] = s^2 \mathcal{L}[y] - s(1) - (-1), \quad \mathcal{L}[y'] = s \mathcal{L}[y] - 1.$$

$$(s^2 + 2s + 2) \mathcal{L}[y] - s + 1 - 2 = \mathcal{L}[\sin(at)].$$

$$\mathcal{L}[y] = \frac{(s+1)}{(s^2 + 2s + 2)} + \frac{1}{(s^2 + 2s + 2)} \mathcal{L}[\sin(at)].$$

Solution decomposition theorem.

Example

Use the Solution Decomposition Theorem to express the solution of

$$y'' + 2y' + 2y = \sin(at), \quad y(0) = 1, \quad y'(0) = -1.$$

Solution: Recall: $\mathcal{L}[y] = \frac{(s+1)}{(s^2+2s+2)} + \frac{1}{(s^2+2s+2)} \mathcal{L}[\sin(at)]$.

But: $\mathcal{L}[y_h] = \frac{(s+1)}{(s^2+2s+2)} = \frac{(s+1)}{(s+1)^2+1} = \mathcal{L}[e^{-t} \cos(t)]$,

and: $\mathcal{L}[y_\delta] = \frac{1}{(s^2+2s+2)} = \frac{1}{(s+1)^2+1} = \mathcal{L}[e^{-t} \sin(t)]$. So,

$$\mathcal{L}[y] = \mathcal{L}[y_h] + \mathcal{L}[y_\delta] \mathcal{L}[g(t)] \Rightarrow y(t) = y_h(t) + (y_\delta * g)(t),$$

So: $y(t) = e^{-t} \cos(t) + \int_0^t e^{-\tau} \sin(\tau) \sin[a(t-\tau)] d\tau. \quad \triangleleft$

Solution decomposition theorem.

Proof: Compute: $\mathcal{L}[y''] + a_1 \mathcal{L}[y'] + a_0 \mathcal{L}[y] = \mathcal{L}[g(t)]$, and recall,

$$\mathcal{L}[y''] = s^2 \mathcal{L}[y] - sy_0 - y_1, \quad \mathcal{L}[y'] = s \mathcal{L}[y] - y_0.$$

$$(s^2 + a_1s + a_0) \mathcal{L}[y] - sy_0 - y_1 - a_1y_0 = \mathcal{L}[g(t)].$$

$$\mathcal{L}[y] = \frac{(s+a_1)y_0 + y_1}{(s^2 + a_1s + a_0)} + \frac{1}{(s^2 + a_1s + a_0)} \mathcal{L}[g(t)].$$

Recall: $\mathcal{L}[y_h] = \frac{(s+a_1)y_0 + y_1}{(s^2 + a_1s + a_0)}$, and $\mathcal{L}[y_\delta] = \frac{1}{(s^2 + a_1s + a_0)}$.

Since, $\mathcal{L}[y] = \mathcal{L}[y_h] + \mathcal{L}[y_\delta] \mathcal{L}[g(t)]$, so $y(t) = y_h(t) + (y_\delta * g)(t)$.

Equivalently: $y(t) = y_h(t) + \int_0^t y_\delta(\tau)g(t-\tau) d\tau. \quad \square$